



BEAMZ
MADE
EAZY

150.164 V1.0

STARCOLOR 54

QUICK **START** GUIDE

CONTROL MENU

MENU			DESCRIPTION
SET UP	Dimmer ALL	000-255	Master dimmer
	Balance	Dimmer Red	000-255
		Dimmer Green	000-255
		Dimmer Blue	000-255
	Key lock	Off	Activate key lock yes/no
		On	
	Remote	Off	Activate IR remote yes/no
		ON	
	Display	30S	Display sleep mode or on
		ON	
	Reset		Reset mode
	Refresh rate	600Hz	Refresh rates
		1200Hz	
		2400HZ	
		900HZ	
	MAX temp	Choose between 30 - 70	Choose max temp
INFO	Software Ver ***		Shows software version
	Working times *****H *M		Shows Working hours
	RDM:*****		Shows RDM address
DMX ADDRESS		000-512	Select a DMX Channel
CHANNEL		3CH,5CH,8CH,13CH	Select a Channel mode
DIM CURVE		Curv1 (2-3-4)	Select a Dim curve
DMX STATE		Hold/ Blackout	Select what to do when there is no DMX signal input.
SLAVE MODE		Slave	Select slave mode
AUTO MODE	Speed	01-31	Select speed auto mode
	Auto	01-31	Select different auto mode
MANUAL MODE	Red	000-255	Adjust dimming
	Green	000-255	Adjust dimming
	Bleu	000-255	Adjust dimming
	Strobe	00-20	Adjust strobe
	Color	01-55	Adjust Color

DMX CHANNELS

3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Red	000-255	Dimmer
2	Green	000-255	Dimmer
3	Blue	000-255	Dimmer

5 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000- 255	Master dimmer
2	Red	000-255	Dimmer
3	Green	000-255	Dimmer
4	Blue	000-255	Dimmer
5	Strobe	000-009	Led blue
		010-255	Strobe (from slow to fast)

8 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000- 255	Master dimmer
2	Red	000-255	Dimmer
3	Green	000-255	Dimmer
4	Blue	000-255	Dimmer
5	Strobe	000-009	No function
		010-255	Strobe (from slow to fast)
6	Static Color	000-009	No function
		010-174	Static color
		175-189	3200k
		190-204	5600k
		205-219	6500k
		220-234	8500k
		235-249	10000k
		250-255	Default
		000-020	No function
		021-030	Auto 1
7	Auto program	031-040	Auto 2
		041-050	Auto 3
		051-060	Auto 4
		061-070	Auto 5
		071-080	Auto 6
		081-090	Auto 7
		091-100	Auto 8
		101-110	Auto 9
		111-120	Auto 10
		121-255	Reserved
8	Auto speed	000-255	Speed slow to fast

13 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000- 255	Master dimmer
2	Dimmer fine	000- 255	Fine control of master dimmer
3	Red	000- 255	Dimmer
4	Red fine	000- 255	Fine control of Red dimmer
5	Green	000- 255	Dimmer
6	Green fine	000- 255	Fine control of Green dimmer
7	Blue	000- 255	Dimmer
8	Blue fine	000- 255	Fine control of Blue dimmer
9	Strobe	000-009	Leds on
		010-255	Strobe (from slow to fast)
		000-009	No function
10	Static color	010-174	Static color
		175-189	3200k
		190-204	5600k
		205-219	6500k
		220-234	8500k
		235-249	10000k
		250-255	Default
11	Auto mode	000-020	No function
		021-030	Auto 1
		031-040	Auto 2
		041-050	Auto 3
		051-060	Auto 4
		061-070	Auto 5
		071-080	Auto 6
		081-090	Auto 7
		091-100	Auto 8
		101-110	Auto 9
		111-120	Auto 10
		121-255	Reserved
12	Auto speed	000-255	Speed slow to fast
13	Dimming curve	000-015	Null
		016-075	Dimming curve 1
		076-135	Dimming curve 2
		136-195	Dimming curve 3
		196-255	Dimming curve 4



Handwriting practice lines consisting of 20 horizontal dotted lines.



Handwriting practice lines consisting of 20 horizontal dotted lines.



Handwriting practice lines consisting of 20 horizontal dotted lines.



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM