



BEAMZ
MADE
EAZY

153.600 V1.2

MULTIACE 3

QUICK START GUIDE

CONTROL MENU

MENU	MODE	DESCRIPTION
Addr	d001-d512	Adres the 8CH mode
Stat	S 01-20	Static colors
Auto	Au 1-6	Auto program
Soun	So 1-6	Sound program
SPEE	SP 1-4	Speed
SEnS	Se1-Se9	MIC sensitivity
SILE	on/oFF	Silent scene by Sound program
Stro	on/oFF	Enable or Disenable the SMD strobe
SLAV	Slave	Slave
InFr	on/oFF	Enable or Disenable IR remote

DMX CHANNELS

CHANNEL	VALUE	DESCRIPTION
1	0-255	Master dimming (0-100%)
2	0-255	Stroboscope (Rate 0-100%)
3	0-9	No function
	10-19	Red
	20-29	Green
	30-39	Blue
	40-49	White
	50-59	Amber
	60-69	Pink
	70-79	Red+ Green
	80-89	Red+ Blue
	90-99	Red+ White
	100-109	Green+ Blue
	110-119	Blue+ White
	120-129	White+ Amber
	130-139	Amber+ Pink
	140-149	Red+ Green+ Blue
	150-159	Green+ Blue+ White
	160-169	Blue+ White+ Amber
	170-179	White+ Amber+ Pink
	180-189	Red+ Blue+ Amber
	190-199	Blue+ White+ Amber
200-255	Red+ Green+ Blue+ White+ Amber+ Pink	
3	0-9	No function
	10-129	Motor clockwise (From slow to fast)
	130-255	Motor counterclockwise (From slow to fast)
5	0-9	UV OFF
	10-255	UV ON
6	0-4	SMD OFF
	5-9	SMD ON
	10-255	SMD stroboscope (Rate 0-100%)
7	0-9	No function
	10-19	Auto program1 (rate)
	20-29	Auto program2 (rate)
	30-39	Auto program3 (rate)
	40-49	Auto program4 (rate)
	50-59	Auto program5 (rate)
	60-69	Auto program6 (rate)
	70-79	Sound program1 (rate)
	80-89	Sound program2 (rate)
	90-99	Sound program3 (rate)
	100-109	Sound program4 (rate)
	110-119	Sound program5 (rate)
120-255	Sound program6 (rate)	
8	0-255	Program 1-6 program speed (From slow to fast)



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

