



**BEAMZ**  
**MADE**  
**EAZY**

150.613 V1.1

**COB150 RGBW**

**QUICK START GUIDE**

# CONTROL MENU

MENU		DESCRIPTION	
<b>DMX MODE</b>	DMX	10CH	ADDR:001-512
		05CH	
		04CH	
		03CH	
<b>STATIC COLORS</b>	STATIC	01-27	Static colors
<b>AUTO</b>	AUTO	01-09	Auto program
<b>SOUND</b>	SOUND	01-09	Sound Program
<b>SPEED</b>	SPEED	01-09	Speed
<b>MIC SENSITIVITY</b>	SENSITIV	01-09	MIC sensitivity
<b>EDIT COLOR</b>	COLOR	R:000-255	Red (0-100%)
		G:000-255	Green (0-100%)
		B:000-255	Blue (0-100%)
		W:000-255	White (0-100%)
<b>COLOR TEMPERATURE</b>	TEMPERAT	1800K	1800K
		2200K	2200K
		2700K	2700K
		3200K	3200K
		4300K	4300K
		5600K	5600K
		6500K	6500K
		8000K	8000K
<b>DIMMING</b>	DIMMING	01-99	Master dimming
<b>FADING</b>	FADING	00-99	Fading Program
<b>FLASH</b>	FLASH	00-99	Flash Program
<b>SILENT SCENE</b>	SILENT	ON/OFF	Silent scene by Sound program
<b>SLAVE</b>	SLAVE	SLAVE MODE	Enable slave mode
<b>INFRARED</b>	INFRARED	ON/OFF	Enable or Disenable IR remote

# DMX CHANNELS

## 3 CH MODE

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	0-255	Red (0-100%)
2		0-255	Green (0-100%)
3		0-255	Blue (0-100%)

## 4 CH MODE

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	0-255	Red (0-100%)
2		0-255	Green (0-100%)
3		0-255	Blue (0-100%)
4		0-255	White (0-100%)

## 5 CH MODE

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Master dimmer	0-255	Master dimming (0-100%)
2	Strobe	0-9	No function
		10-255	Stroboscope (Rate 0-100%)
3	Static colors	0-9	No function
		10-19	Red
		20-29	Green
		30-39	Blue
		40-49	White
		50-59	Yellow
		60-69	Magenta
		70-79	Cyan
		80-89	Dark orange
		90-99	Green yellow
		100-109	Salmon
		110-119	Turquoise
		120-129	Light Green
		130-139	Orange
		140-149	Straw
		150-159	Lavender
		160-169	Light blue
		170-179	Dark blue
		180-189	Pink
		190-255	Full on
4	Auto prog	0-9	No function
		10-19	Auto program1
		20-29	Auto program2
		30-39	Auto program3
		40-49	Auto program4
		50-59	Auto program5
		60-69	Auto program6
		70-79	Auto program7

		80-89	Auto program8
		90-99	Auto program9
		100-109	Sound Program1
		110-119	Sound Program2
		120-129	Sound Program3
		130-139	Sound Program4
		140-149	Sound Program5
		150-159	Sound Program6
		160-169	Sound Program7
		170-179	Sound Program8
		180-255	Sound Program9
5	Speed auto prog	0-255	Auto and Sound program speed (Slow-fast)

## 10 CH MODE

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Master Dimmer	0-255	Master dimming (0-100%)
2	Strobe	0-9	No function
		10-255	Stroboscope (Rate 0-100%)
3	Manual	0-255	Red (0-100%)
4		0-255	Green (0-100%)
5		0-255	Blue (0-100%)
6		0-255	White (0-100%)
7		Static colors	0-9
	10-19		Red
	20-29		Green
	30-39		Blue
	40-49		White
	50-59		Yellow
	60-69		Magenta
	70-79		Cyan
	80-89		Dark orange
	90-99		Green yellow
	100-109		Salmon
	110-119		Turquoise
	120-129		Light Green
	130-139		Orange
	140-149		Straw
	150-159		Lavender
	160-169		Light blue
	170-179		Dark blue
	180-189		Pink
	190-255	Full on	
8	Auto prog	0-9	No function
		10-19	Auto program1
		20-29	Auto program2
		30-39	Auto program3
		40-49	Auto program4
		50-59	Auto program5
		60-69	Auto program6
		70-79	Auto program7

		80-89	Auto program8
		90-99	Auto program9
		100-109	Sound Program1
		110-119	Sound Program2
		120-129	Sound Program3
		130-139	Sound Program4
		140-149	Sound Program5
		150-159	Sound Program6
		160-169	Sound Program7
		170-179	Sound Program8
		180-255	Sound Program9
9	Speed auto prog	0-255	Auto and Sound program speed (Slow-fast)
10	Color temprature	0-9	No function
		10-39	1800K
		40-69	2200K
		70-99	2700K
		100-129	3200K
		130-159	4300K
		160-189	5600K
		190-219	6500K
		220-255	8000K



A series of horizontal dotted lines spanning the width of the page, providing a guide for handwriting practice.





A series of horizontal dotted lines for writing, spanning the width of the page.



# BEAMZ

**YOUR FUTURE**  
**YOUR SKILLS**  
**YOUR PLATFORM**  
**YOUR PARTY**  
**YOUR EVENT**



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

