



BEAMZ
MADE
EAZY

150.120 V2.0

MHL1912Z

QUICK START GUIDE

CONTROL MENU

| MENU | FUNCTION | VALUE | DESCRIPTION |
|----------------|--------------|-----------------|---------------------|
| Setting | DMX Addr | 001-512 | DMX address setting |
| | Encpder | Yes/No | Autocorrect |
| | PanREV | Yes/No | Reverse Pan |
| | TiltREV | Yes/No | Reverse Tilt |
| Runmode | Runmode | DMX/AUTO/SOUND | Auto program |
| | Channel | 15CH or 23CH | Channel mode |
| Display | Language | EN/中文 | Set language |
| | Reverse | Yes /No | Reverse Display |
| | Screensavers | Off/15S/30S/60S | Dark display mode |
| Factory | Pan | 128 | Set value |
| | Tilt | 128 | Set value |
| | Focus | 128 | Set value |
| | Red | 220 | Set value |
| | Green | 220 | Set value |
| | Blue | 220 | Set value |
| | White | 220 | Set value |
| | Logo | | No function |

DMX CHANNELS

15 Channel mode

| CHANNEL | FUNCTION | VALUE | DESCRIPTION |
|---------|---------------------|-----------|-------------------------------------|
| 1 | Pan | 000-255 | Adjust Pan function |
| 2 | Pan Fine | 000-255 | Adjust Fine Pan function |
| 3 | Tilt | 000-255 | Adjust Tilt function |
| 4 | Tilt Fine | 000-255 | Adjust Fine Tilt function |
| 5 | P/T Speed | 000-255 | Adjust the P/T speed |
| 6 | Zoom | 000-255 | Adjust the Zoom from wide to narrow |
| 7 | Dimmer | 000-255 | Adjust the dimmer funtion |
| 8 | Strobe | 000-255 | Adjust strobe function |
| 9 | Red | 000-255 | Adjust red colour |
| 10 | Green | 000-255 | Adjust green colour |
| 11 | Blue | 000-255 | Adjust blue colour |
| 12 | White | 000-255 | Adjust white colour |
| | | 000-029 | No Function |
| | | 030-039 | Red |
| | | 040-049 | Green |
| | | 050-059 | Blue |
| | | 060-069 | Red+Green |
| | | 070-079 | Red+Blue |
| | | 080-089 | Green+Blue |
| 13 | Function Mode | 090 - 139 | RGBW |
| | | 140 - 169 | Color pulse change |
| | | 170 - 199 | Color gradual change |
| | | 200-208 | Color jump change |
| | | 209- 218 | Auto running effect 1 |
| | | 219 - 228 | Auto running effect 2 |
| | | 229 -238 | Auto running effect 3 |
| | | 239 -255 | Auto running effect 4 |
| 14 | Function Mode Speed | 000-255 | Adjust macro function |
| 15 | Reset (255) | 000-255 | Reset function |

23 Channel Mode

| CHANNEL | FUNCTION | VALUE | DESCRIPTION |
|---------|---------------------|-----------|-------------------------------------|
| 1 | Pan | 000-255 | Adjust Pan function |
| 2 | Pan Fine | 000-255 | Adjust Fine Pan function |
| 3 | Tilt | 000-255 | Adjust Tilt function |
| 4 | Tilt Fine | 000-255 | Adjust Fine Tilt function |
| 5 | P/T Speed | 000-255 | Adjust the P/T speed |
| 6 | Zoom | 000-255 | Adjust the Zoom from wide to narrow |
| 7 | Dimmer (0-100%) | 000-255 | Adjust the dimmer function |
| 8 | Strobe | 000-255 | Adjust strobe function |
| 9 | Red | 000-255 | first Section |
| 10 | Green | 000-255 | first Section |
| 11 | Blue | 000-255 | First Section |
| 12 | White | 000-255 | First Section |
| 13 | Red | 000-255 | Second section |
| 14 | Green | 000-255 | Second section |
| 15 | Blue | 000-255 | Second section |
| 16 | White | 000-255 | Second section |
| 17 | Red | 000-255 | Third Section |
| 18 | Green | 000-255 | Third Section |
| 19 | Blue | 000-255 | Third Section |
| 20 | White | 000-255 | Third Section |
| | | 000-029 | No Function |
| | | 030-039 | Red |
| | | 040-049 | Green |
| | | 050-059 | Blue |
| | | 060-069 | Red+Green |
| | | 070-079 | Red+Blue |
| | | 080-089 | Green+Blue |
| 21 | Function Mode | 090 - 139 | RGBW |
| | | 140 - 169 | Color pulse change |
| | | 170 - 199 | Color gradual change |
| | | 200-208 | Color jump change |
| | | 209- 218 | Auto running effect 1 |
| | | 219 - 228 | Auto running effect 2 |
| | | 229 -238 | Auto running effect 3 |
| | | 239 -255 | Auto running effect 4 |
| 22 | Function Mode Speed | 000-255 | Select one of the macro functions |
| 23 | Reset (255) | 000-255 | Reset function |



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

