



BEAMZ
MADE
EAZY

153.282 V1.0

LMB1040IP

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION		
ADDRESS	001-512	DMX address setting		
	DMX512	Auto program		
	Auto 1			
DMX MODE	Auto 2			
	13CH	Select DMX mode		
	26CH			
	27CH			
	28CH			
	29CH			
	46CH			
	47CH			
TEST	All Test	Test all		
	Tilt Test	Tilt Test		
	Lamp Test	Lamp Test		
SET	Display	Display time	ON	Display will go off after 30 seconds
			OFF	
	Display Rev		ON	Reverse display
			OFF	
	Key lock		ON	Key lock after 30 seconds
			OFF	
	Disp flash		ON	Display flashes when there is no DMX input
			OFF	
	Tilt Reverse		ON	
			OFF	
	No DMX Status		Black	
			Hold	
	Dim Speed		Fast	
			Slow	
	Dim Curve		Linear	
			Square	
			Inv. Sq.	
			S-Curve	
INFO	Time info	Power on	0000:00	Display the time in use
	Version	xxxxxx	Software version	
MANUAL	Zoom	000-255	Manual setting	
	Tilt	000-255		
	Func.	000-255		
	Dimmer	000-255		
	Strobe	000-255		
	Macro	000-255		
	Red	000-255		
	Green	000-255		
	Blue	000-255		
	White	000-255		
	Chase	000-255		
	Speed	000-255		
	Red1	000-255		
	Green1	000-255		
	Blue1	000-255		

	White1	000-255	
			
	Red10	000-255	
	Green10	000-255	
	Blue10	000-255	
	White10	000-255	
RESET	All Reset	No	Reset all
		Yes	

DMX CHANNELS

13 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Tilt
2		000-255	Tilt fine
3	SET 1 COLOR(FIXED)	000-007	Colors adjustable via RGB
		008-015	Color 01-red
		016-023	Color 02- amber
		024-031	Color 03-warm yellow
		032-039	Color 04-yellow
		040-047	Color 05-green
		048-055	Color 06-Turquoise
		056-063	Color 07-cyan
		064-071	Color 08-blue
		072-079	Color 09-lavender
		080-087	Color 10-malve
		088-095	Color 11-magenta
		096-103	Color 12-Pink
		104-111	White-CTO (3200K)
		112-119	White (5600K)
		120-127	White-CTB (7200K)
		128-255	Rainbow effect
4		000-255	Set 1 red, color mixing system
5		000-255	Set 1 green, color mixing system
6		000-255	Set 1 blue, color mixing system
7		000-255	Set 1 white, color mixing system
8	SHUTTER	000-009	Shutter closed
		010-109	Shutter pulse random, slow to fast
		110-239	Strobe effect, slow to fast
		240-255	Shutter closed
9		000-255	Intensity
10		000-250	No function
		251-255	Reset
11		000-255	Pattern movement
12		000-255	Zoom, wide(flood)-Narrow(spot)
13		000-255	Set 1 pattern select

26 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Tilt
2		000-255	Tilt fine
3	SHUTTER	000-009	Shutter closed
		010-109	Shutter pulse random, slow to fast
		110-239	Strobe effect, slow to fast
		240-255	Shutter closed
4		000-255	Intensity
5		000-250	No function
		251-255	Reset
6		000-255	Zoom, wide(flood)-Narrow(spot)
7		000-255	Set 1&2 red, color mixing system
8		000-255	Set 1&2 green, color mixing system
9		000-255	Set 1&2 blue, color mixing system

10	000-255	Set 1&2 white, color mixing system
11	000-255	Set 3&4 red, color mixing system
12	000-255	Set 3&4 green, color mixing system
13	000-255	Set 3&4 blue, color mixing system
14	000-255	Set 3&4 white, color mixing system
15	000-255	Set 5&6 red, color mixing system
16	000-255	Set 5&6 green, color mixing system
17	000-255	Set 5&6 blue, color mixing system
18	000-255	Set 5&6white, color mixing system
19	000-255	Set 7&8 red, color mixing system
20	000-255	Set 7&8 green, color mixing system
21	000-255	Set 7&8 blue, color mixing system
22	000-255	Set 7&8 white, color mixing system
23	000-255	Set 9&10 red, color mixing system
24	000-255	Set 9&10 green, color mixing system
25	000-255	Set 9&10 blue, color mixing system
26	000-255	Set 9&10 white, color mixing system

27 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	SHUTTER	000-255	Tilt
2		000-255	Tilt fine
3		000-009	Shutter closed
		010-109	Shutter pulse random, slow to fast
		110-239	Strobe effect, slow to fast
		240-255	Shutter closed
4		000-255	Intensity
5		000-255	Intensity 16bit
6		000-250	No function
		251-255	Reset
7		000-255	Zoom,wide[flood]-Narrow[spot]
8		000-255	Set 1&2 red, color mixing system
9		000-255	Set 1&2 green, color mixing system
10		000-255	Set 1&2 blue, color mixing system
11		000-255	Set 1&2 white, color mixing system
12		000-255	Set 3&4 red, color mixing system
13		000-255	Set 3&4 green, color mixing system
14		000-255	Set 3&4 blue, color mixing system
15		000-255	Set 3&4 white, color mixing system
16		000-255	Set 5&6 red, color mixing system
17		000-255	Set 5&6 green, color mixing system
18		000-255	Set 5&6 blue, color mixing system
19		000-255	Set 5&6white, color mixing system
20		000-255	Set 7&8 red, color mixing system
21		000-255	Set 7&8 green, color mixing system
22		000-255	Set 7&8 blue, color mixing system
23		000-255	Set 7&8 white, color mixing system
24		000-255	Set 9&10 red, color mixing system
25		000-255	Set 9&10 green, color mixing system
26		000-255	Set 9&10 blue, color mixing system
27		000-255	Set 9&10 white, color mixing system

28 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Tilt
2		000-255	Tilt fine
3			Zoom,wide(flood)-Narrow(spot)
4	SET 1 COLOR(FIXED)	000-007	Colors adjustable via RGB
		008-015	Color 01-red
		016-023	Color 02- amber
		024-031	Color 03-warm yellow
		032-039	Color 04-yellow
		040-047	Color 05-green
		048-055	Color 06-Turquoise
		056-063	Color 07-cyan
		064-071	Color 08-blue
		072-079	Color 09-lavender
		080-087	Color 10-malve
		088-095	Color 11-magenta
		096-103	Color 12-Pink
		104-111	White-CTO (3200K)
		112-119	White (5600K)
		120-127	White-CTB (7200K)
		128-255	Rainbow effect
5		000-255	Set 1 red, color mixing system
6		000-255	Set 1 green, color mixing system
7		000-255	Set 1 blue, color mixing system
8		000-255	Set 1 white, color mixing system
9		000-255	Set 1 intensity
10	SHUTTER	000-009	Shutter closed
		010-109	Shutter pulse random, slow to fast
		110-239	Strobe effect, slow to fast
		240-255	Shutter closed
11		000-255	Intensity
12		000-250	No function
		251-255	Reset
13		000-255	Set 2 color :Values see channel 4
14		000-255	Set 2 red, color mixing system
15		000-255	Set 2 green, color mixing system
16		000-255	Set 2 blue, color mixing system
17		000-255	Set 2 white, color mixing system
18		000-255	Set 2 intensity
19		000-255	Set 3 color: values see channel 4
20		000-255	Set 3 red, color mixing system
21		000-255	Set 3 green, color mixing system
22		000-255	Set 3 blue, color mixing system
23		000-255	Set 3 white, color mixing system
24		000-255	Set 3 intensity
25		000-255	Set 1 pattern select
26		000-255	Pattern movement
27		000-255	Set 2 pattern select
28		000-255	26ch pattern movement Speed, fast to slow

29 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1		000-255	Tilt
2		000-255	Tilt fine
3		000-255	Zoom,wide(flood)-Narrow(spot)
4	SET 1 COLOR(FIXED)	000-007	Colors adjustable via RGB
		008-015	Color 01-red
		016-023	Color 02- amber
		024-031	Color 03-warm yellow
		032-039	Color 04-yellow
		040-047	Color 05-green
		048-055	Color 06-Turquoise
		056-063	Color 07-cyan
		064-071	Color 08-blue
		072-079	Color 09-lavender
		080-087	Color 10-malve
		088-095	Color 11-magenta
		096-103	Color 12-Pink
		104-111	White-CTO (3200K)
		112-119	White (5600K)
		120-127	White-CTB (7200K)
		128-255	Rainbow effect
5		000-255	Set 1 red, color mixing system
6		000-255	Set 1 green, color mixing system
7		000-255	Set 1 blue, color mixing system
8		000-255	Set 1 white, color mixing system
9		000-255	Set 1 intensity
10	SHUTTER	000-009	Shutter closed
		010-109	Shutter pulse random, slow to fast
		110-239	Strobe effect, slow to fast
		240-255	Shutter closed
11		000-255	Intensity
12		000-255	Intensity 16bit
13		000-250	No function
		251-255	Reset
14		000-255	Set 2 color :Values see channel 4
15		000-255	Set 2 red, color mixing system
16		000-255	Set 2 green, color mixing system
17		000-255	Set 2 blue, color mixing system
18		000-255	Set 2 white, color mixing system
19		000-255	Set 2 intensity
20		000-255	Set 3 color: values see channel 4
21		000-255	Set 3 red, color mixing system
22		000-255	Set 3 green, color mixing system
23		000-255	Set 3 blue, color mixing system
24		000-255	Set 3 white, color mixing system
25		000-255	Set 3 intensity
26		000-255	Set 1 pattern select
27		000-255	Pattern movement
28		000-255	Set 2 pattern select
29		000-255	27ch pattern movement Speed, fast to slow

46 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	SHUTTER	000-255	Tilt
2		000-255	Tilt fine
3		000-009	Shutter closed
		010-109	Shutter pulse random, slow to fast
		110-239	Strobe effect, slow to fast
		240-255	Shutter closed
4		000-255	Intensity
5		000-250	No function
		251-255	Reset
6		000-255	Zoom,wide(flood)-Narrow(spot)
7		000-255	Set 1 red, color mixing system
8		000-255	Set 1 green, color mixing system
9		000-255	Set 1 blue, color mixing system
10		000-255	Set 1 white, color mixing system
11		000-255	Set 2 red, color mixing system
12		000-255	Set 2 green, color mixing system
13		000-255	Set 2 blue, color mixing system
14		000-255	Set 2 white, color mixing system
15		000-255	Set 3 red, color mixing system
16		000-255	Set 3 green, color mixing system
17		000-255	Set 3 blue, color mixing system
18		000-255	Set 3 white, color mixing system
19		000-255	Set 4 red, color mixing system
20		000-255	Set 4 green, color mixing system
21		000-255	Set 4 blue, color mixing system
22		000-255	Set 4 white, color mixing system
23		000-255	Set 5 red, color mixing system
24		000-255	Set 5 green, color mixing system
25		000-255	Set 5 blue, color mixing system
26		000-255	Set 5 white, color mixing system
27		000-255	Set 6 red, color mixing system
28		000-255	Set 6 green, color mixing system
29		000-255	Set 6 blue, color mixing system
30		000-255	Set 6 white, color mixing system
31		000-255	Set 7 red, color mixing system
32		000-255	Set 7 green, color mixing system
33		000-255	Set 7 blue, color mixing system
34		000-255	Set 7 white, color mixing system
35		000-255	Set 8 red, color mixing system
36		000-255	Set 8 green, color mixing system
37		000-255	Set 8 blue, color mixing system
38		000-255	Set 8 white, color mixing system
39		000-255	Set 9 red, color mixing system
40		000-255	Set 9 green, color mixing system
41		000-255	Set 9 blue, color mixing system
42		000-255	Set 9 white, color mixing system
43		000-255	Set 10 red, color mixing system
44		000-255	Set 10 green, color mixing system
45		000-255	Set 10 blue, color mixing system
46		000-255	Set 10 white, color mixing system

47 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	SHUTTER	000-255	Tilt
2		000-255	Tilt fine
3		000-009	Shutter closed
		010-109	Shutter pulse random, slow to fast
		110-239	Strobe effect, slow to fast
		240-255	Shutter closed
4		000-255	Intensity
5		000-255	Intensity 16bit
6		000-250	No function
		251-255	Reset
7		000-255	Zoom,wide[flood]-Narrow[spot]
8		000-255	Set 1 red, color mixing system
9		000-255	Set 1 green, color mixing system
10		000-255	Set 1 blue, color mixing system
11		000-255	Set 1 white, color mixing system
12		000-255	Set 2 red, color mixing system
13		000-255	Set 2 green, color mixing system
14		000-255	Set 2 blue, color mixing system
15		000-255	Set 2 white, color mixing system
16		000-255	Set 3 red, color mixing system
17		000-255	Set 3 green, color mixing system
18		000-255	Set 3 blue, color mixing system
19		000-255	Set 3 white, color mixing system
20		000-255	Set 4 red, color mixing system
21		000-255	Set 4 green, color mixing system
22		000-255	Set 4 blue, color mixing system
23		000-255	Set 4 white, color mixing system
24		000-255	Set 5 red, color mixing system
25		000-255	Set 5 green, color mixing system
26		000-255	Set 5 blue, color mixing system
27		000-255	Set 5 white, color mixing system
28		000-255	Set 6 red, color mixing system
29		000-255	Set 6 green, color mixing system
30		000-255	Set 6 blue, color mixing system
31		000-255	Set 6 white, color mixing system
32		000-255	Set 7 red, color mixing system
33		000-255	Set 7 green, color mixing system
34		000-255	Set 7 blue, color mixing system
35		000-255	Set 7 white, color mixing system
36		000-255	Set 8 red, color mixing system
37		000-255	Set 8 green, color mixing system
38		000-255	Set 8 blue, color mixing system
39		000-255	Set 8 white, color mixing system
40		000-255	Set 9 red, color mixing system
41		000-255	Set 9 green, color mixing system
42		000-255	Set 9 blue, color mixing system
43		000-255	Set 9 white, color mixing system
44		000-255	Set 10 red, color mixing system
45		000-255	Set 10 green, color mixing system
46		000-255	Set 10 blue, color mixing system



10



BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM